

BVS 15-99



BVS 15-99

Small size remote powered D3 amplifier BVS 15-99 is an excellent solution for discharging the cable networks. 15VDC or 18VAC supply voltage is supplied to a coaxial cable. Due to its small size and the possibility of remote input BVS 15-99 can be installed in locations that are subject to the amplifier can not. The characteristics of the price leader in its class.

Rating: Not Rated Yet
3-5 Days

[Ask a question about this product](#)

Description

Features

- ? Large output level
- ? Built-in reverse amplifier
- ? The operating voltage remote input
- ? The size of just the amplifier 125 mm W, 85 mm H 45 mm

Technical information

- ? Frequency range 88-862 MHz
- ? Maximum Gain 38 dB
- ? Maximum output level of 103 dB?V 42 Ch. CSO / CTB
- ? Tilt adjustment 0 - 18 dB
- ? Return Path Frequency Range 5-65 MHz
- ? The reverse amplification max. 28 dB
- ? The operating voltage of 15 VDC / 18 VAC
- ? Power consumption 8W

